

## Homework # 6, due on Friday, February 24

[1] (a) Show in discrete variables that

$$\mathcal{F}\left(f(x, y)e^{2\pi i(u_0 \frac{x}{M} + v_0 \frac{y}{N})}\right) = F(u - u_0, v - v_0),$$

where  $F = \mathcal{F}(f)$ .

(b) Using (a), deduce the formula used in shifting the center of the transform by multiplication with  $(-1)^{x+y}$ , when  $u_0 = M/2$  and  $v_0 = N/2$ , with  $M$  and  $N$  even positive integers.

[2]

(a) Show the translation property

$$\mathcal{F}\left(f(x - x_0, y - y_0)\right) = F(u, v)e^{-2\pi i(x_0 u/M + y_0 v/N)},$$

where  $F(u, v) = \mathcal{F}(f(x, y))$ .

(b) Consider the linear difference operator  $g(x, y) = f(x + 1, y) - f(x, y)$ . Obtain the filter transfer function,  $H(u, v)$ , for performing the equivalent process in the frequency domain.

[3] Prove the validity of the discrete convolution theorem in one variable (you may need to use the translation properties).

[4] Assume that  $f(x)$  is given by the discrete IFT formula in one dimension. Show the periodicity property  $f(x) = f(x + kM)$ , where  $k$  is an integer.

[5] (a) Implement the Gaussian lowpass filter in Eq. (4.3-8), using a radius  $D_0 = 25$ , and apply the algorithm to Fig4.11(a).

(b) Highpass the input image used in (a), using a highpass Gaussian filter of radius  $D_0 = 25$  (see eq. (4.4-4)).